PUBLIC ADDRESS / MIXERS / MONO

MX-848

MONO MIXER







- Excellent features
- Wide variety of inputs
- Priority paging
- Phantom power supply

+ Info:
https://fonestar.com/MX-848

ESPECIALLY RECOMMENDED IN:



All sectors

DESCRIPTION


Analogue mixer. 6 mono channels. 3 stereo channels 1 stereo or mono output.


TECHNICAL CHARACTERISTICS


FEATURES	Mixer/preamplifier. Microphone input with paging priority. Phantom power supply. LED output level indicators.
INPUTS	6 balanced mics./lines, combo (XLR and 6.3 mm jack), 1,500 Ohm 7.7 mV y 10,000 Ohm 775 mV switchable 3 stereo aux, 2 x RCA, 10,000 Ohm 2.4 V RMS
OUTPUTS	1 balanced stereo master, XLR 120 Ohm 775 mV RMS 1 balanced mono master, 6.3 mm jack, 120 Ohm 775 mV RMS 1 balanced mono mix out, 6.3 mm jack 120 Ohm 775 mV RMS 1 line out, 2 x RCA 120 Ohm 775 mV RMS
CONTROLS	Tone: master output bass, mid and treble Volume: inputs 1 to 12 and general volume (stereo and mono master)
RESPONSE	20-22,000 Hz
DISTORTION	Harmonic: < 0.05% at 1 kHz
S/N RATIO	Microphones > 103 dB Aux/Line > 103 dB
PHANTOM	18 V in mics. 1 to 6, selectable
PRIORITY	Mic. 1 depending on signal level, selectable
POWER SUPPLY	230 V AC, 18 W and 24 V DC, 500 mA 115 v AC on request
DIMENSIONS	483 x 44 x 220 mm depth. 1 U 19" rack
WEIGHT	3 kg



+ Info:
https://fonestar.com/MX-848







	Model	Description	Units	Scale
FONESTAR	MX-848	MONO MIXER	mm	1:2