PUBLIC ADDRESS / MIXERS / MONO

MX-867RU

MONO MIXER



- Excellent features
- Matrix allocation of 5 input channels to 4 output zones
- Priority paging
- Phantom power supply
- Remote volume control

+ Info:
https://fonestar.com/MX-867RU

ESPECIALLY RECOMMENDED IN:



All sectors

DESCRIPTION

Matrix analogue mixer. 5 input channels to 4 output zones. USB/SD/FM player.

TECHNICAL CHARACTERISTICS

FEATURES	Mixer/preamplifier. Microphone input with paging priority. Matrix allocation of 5 input channels to 4 output zones. USB/SD player. Digital FM radio tuner. 4 speaker zones with independent volume control. Remote zone volume control. Phantom power supply.
INPUTS	1 balanced microphone, 6.3 mm stereo jack, 12 mV RMS 1 balanced mic., combo (XLR and 6.3 mm jack), 12 mV RMS 2 balanced mics./lines combo (XLR and 6.3 mm jack) adjustable, 12 mV RMS and 640 mV RMS 1 stereo aux, 2 x RCA, 230 mV RMS 1 stereo aux, 3.5 m jack, 450 mV RMS
OUTPUTS	4 balanced zones, XLR, 2.5 V RMS Remote volume control for the zones 1 stereo monitor, 6.3 mm jack, 1 V RMS
CONTROLS	4 micro allocation switches for zones 1 to 4 Inputs 1 to 4: volume control Inputs 2 and 3: gain control Zones 1 to 4: volume control Monitor: volume control and zone selection USB/SD player FM tuner
RESPONSE	20-20,000 Hz
DISTORTION	Harmonic: < 0.2 % to 1 kHz
S/N RATIO	Microphones > 65 dB Aux/Line > 80 dB



+ Info:
https://fonestar.com/MX-867RU

PHANTOM	48 V in mics. 2 and 3, selectable
PRIORITY	Mic. 1 input level priority, selectable
POWER SUPPLY	230/115 V AC, 9 W
DIMENSIONS	483 x 44.5 x 200 mm depth. 1 U 19" rack
WEIGHT	3.15 kg



+ Info:
https://fonestar.com/MX-867RU